

The specification of the adaptor supplied with the product is listed below. Please cross check the **Adaptor model number** found on the adaptor itself with the information in the tables below.

Manufacturer address and registration number	UK: Spectrum Brands (UK) Limited, Regent Mill, Fir Street, Failsworth, Manchester M35 0HS Company number: 02394603					
	EU: VARTA Consumer Batteries GmbH & Co KGaA, Alfred-Krupp-Strasse 9, 73479 Ellwangen, Germany Court of Record Ulm, HRB 510581					
Adapter model number	PA-0510U PA-0510K PA-0510E	PA-3215U PA-3215E	PA1204U PA1204K PA1204E	PA-4515U PA-4515E	PA-0401U PA-0401E	PA-0505U PA-0505K PA-0505E
Input voltage	100 - 240 V~	100 - 240 V~	100 - 240 V~	100 - 240 V~	100 - 240 V~	100 - 240 V~
Input AC Frequency	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz
Output voltage	5.0 V ---	3.2 V ---	12.0 V ---	4.5 V ---	4.0 V ---	5.0 V ---
Output current	1.0 A	1.5 A	0.4 A	1.5 A	0.1 A	0.5 A
Output power	5.0 W	4.8 W	4.8 W	6.75 W	0.4 W	2.5 W
Average active efficiency	≥73.7%	≥73.31%	≥77.59%	≥75.88%	≥36.0%	≥73.16%
Efficiency at 10%	-	-	-	-	-	-
No load power consumption	≤0.1W	≤0.1W	≤0.1W	≤0.1W	≤0.1W	≤0.1W

Manufacturer address and registration number	UK: Spectrum Brands (UK) Limited, Regent Mill, Fir Street, Failsworth, Manchester M35 0HS Company number: 02394603				
	EU: VARTA Consumer Batteries GmbH & Co KGaA, Alfred-Krupp-Strasse 9, 73479 Ellwangen, Germany Court of Record Ulm, HRB 510581				
Adapter model number	SW-040010BS SW-040010BST SW-040010EU	SW-040010BSL SW-040010EUL	SW-047010BS SW-047010UK SW-047010EU	HKP818-1201200dB HKP818-1201200dV	HK28BA-5.0-350 HK28GA-5.0-350
Input voltage	100 - 240 V~	100 - 240 V~	100 - 240 V~	100 - 240 V~	220 - 240 V~
Input AC Frequency	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz
Output voltage	4.0 V ---	4.0 V ---	4.7 V ---	12.0 V ---	5.0 V ~
Output current	0.1 A	0.1 A	0.1 A	1.2 A	0.35 A
Output power	0.4 W	0.4 W	0.47 W	14.4 W	1.75 W
Average active efficiency	≥39.5%	≥39.5%	≥40.4%	≥83.92%	≥70.73%
Efficiency at 10%	-	-	-	≥73.92%	-
No load power consumption	≤0.1W	≤0.1W	≤0.1W	≤0.1W	≤0.21W

Manufacturer address and registration number	UK: Spectrum Brands (UK) Limited, Regent Mill, Fir Street, Failsworth, Manchester M35 0HS Company number: 02394603				
	EU: VARTA Consumer Batteries GmbH & Co KGaA, Alfred-Krupp-Strasse 9, 73479 Ellwangen, Germany Court of Record Ulm, HRB 510581				
Adapter model number	SW-120060EU SW-120060BS	PA-0515U PA-0515E	PA-04701U PA-04701K PA-04701E	SW-030100EU SW-030100BS	SW-300025EU SW-300025BS
Input voltage	100 - 240 V~	100 - 240 V~	100 - 240 V~	100 - 240 V~	100 - 240 V~
Input AC Frequency	50/60Hz	50/60Hz	50/60Hz	50/60Hz	50/60Hz
Output voltage	12.0 V ---	5.0 V ---	4.7 V ---	3.0 V ---	30.0 V ---
Output current	0.6 A	1.5 A	0.1 A	1.0 A	0.25 A
Output power	7.2 W	7.5 W	0.47 W	3.0 W	7.5 W
Average active efficiency	≥80.01%	≥76.65%	≥39.5%	≥69.64%	≥80.3%
Efficiency at 10%	-	-	-	-	-
No load power consumption	≤0.1W	≤0.1W	≤0.1W	≤0.1W	≤0.1W